




1. DETECTOR SHOULD BE MOUNTED AS FOLLOWS:

- A. THE DETECTOR SCINTILLATOR SHOULD BE SET AT THE DETECTOR GAP RECOMMENDED ON THE SIZE SHEET. IF A SIZE SHEET IS NOT AVAILABLE, VEGA RECOMMENDS 50mm [2"] FOR VESSELS WITH MAXIMUM SURFACE TEMPERATURE LESS THAN 60°C AND AT LEAST 150mm [6"] FOR VESSELS WITH MAXIMUM SURFACE TEMPERATURE GREATER THAN 60°C. THIS SPACING IS FROM THE VESSEL'S EXTREME OUTER SURFACE (INSULATION, SHEATHING, ETC.) TO THE SCINTILLATOR SURFACE.
- IF THE TRANSMITTER IS TO BE USED FOR AMBIENT X-RAY PROTECTION, THEN IT SHOULD BE MOUNTED OUTSIDE OF OF THE RADIATION FIELD USED FOR THE MEASUREMENT.
- IN THE MULTI DENSITY ARRAY (MDA) SYSTEMS, THE X-RAY PROTECTION TRANSMITTER CAN BE MOUNTED ON THE VESSEL PLATFORM OR ON THE VERTICAL MOUNTING POLE, AS FAR AS POSSIBLE FROM THE DENSITY MEASUREMENT **TRANSMITTERS**
- D. DO NOT REMOVE ANY INSULATION FROM THE VESSEL DURING INSTALLATION.
- E. DO NOT PLACE ANY MATERIAL BETWEEN THE VESSEL'S EXTREME OUTER SURFACE AND THE
- SCINTILLATOR UNLESS DIRECTED BY VEGA.

 F. MAKE SURE PROCESS MATERIAL OR OTHER FOREIGN MATTER CANNOT ACCUMULATE BETWEEN VESSEL AND SCINTILLATOR.

 2. APPROXIMATE WEIGHTS 4.1 kg [9 lb] ALUMINIUM HOUSING OR 9.1 kg [20 lb] STAINLESS STEEL HOUSING



15√∆'

www.vega.com

1:3

)riginalforma

size of oria

В

Achtung: Diese Zeichnung stellt die zum Zeitpunkt der Konfiguration gültige Geräteausführung dar. Sie wurde automatisch erstellt, spätere Konfiguration können hiervon abweichen. Attention: This drawing shows the valid instrument version on the configuration date. It was created automatically, later configurations may vary.

応 MB6881-US-PC-3

Model Code

POINTRAC 31 (1.8")

Datum/Date 2019-12-3

Alle Bemaßungen in mm [inch] / All dimensions are mm [inches]